

NOARK

AXFD11

Auxiliary contact (microswitch) - 1314052 - Ex9CKT - mounts on 20-40A 3P cont. - 1 SPDT per side - side mounting

Auxiliary contact block / microswitch block - mounts on 20-40A 3P cont. - NOARK (Ex9CKT series) - 1 SPDT per side - Screw connection - side mounting - equivalent to 1314052

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Auxiliary contact
Product series / family name	Industrial controls > Contactors > Definite purpose contactors > Accessories > Auxiliary contacts
Sub-range name	Ex9CKT series
Functions	Auxiliary contact block / microswitch block
Design	mounts on 20-40A 3P cont.
Rated current	3A (drop-out at 120Vac) 1.5A (drop-out at 240Vac) 0.75A (drop-out at 480Vac) 0.6A (drop-out at 600Vac) 30A (pick-up at 120Vac) 15A (pick-up at 240Vac) 7.5A (pick-up at 480Vac) 6A (pick-up at 600Vac) 10A (continuous at 120Vac/240Vac/480Vac/600Vac) 15A (125Vac or 250Vac) 4A (120Vac on lamp load) 0.5A (125Vdc) 0.25A (250Vdc)
Connection type	Screw connection
Mounting mode	side mounting
Normally Open (NO) auxliary contacts	1 NO contacts
Normally Closed (NC) auxiliary contacts	1 NC contacts

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

AXFD11

Auxiliary contact (microswitch) - 1314052 - Ex9CKT - mounts on 20-40A 3P cont. - 1 SPDT per side - side mounting

Contacts type	1 SPDT per side
Order code / Manufacturer SKU	AXFD11 1314052
Manufacturer product status	Commercialized
Equivalent to	1314052

Documents

NOARK - Industrial controls - Catalog.pdf

Access to all NOARK drawings

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com