

NOARK

MD12NC

Motor operator - 1800310 - 3200A frame - 110-130Vdc/ac - for 3200A ACB/switch disconnector

Charging motor / remote operator - for A32/ASD32 (3200A) frame size - NOARK (A32 series) - 94-143Vac (110Vac-130Vac nom.) / 94-143Vdc (110Vdc-130Vdc nom.) supply voltage - equivalent to 1800310

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Charging motor
Product series / family name	Electrical protection > ACBs and disconnector switches accessories > Motor operators
Sub-range name	A32 series
Functions	Charging motor / remote operator
Supply voltage (AC)	94-143Vac (110Vac-130Vac nom.)
Supply voltage (DC)	94-143Vdc (110Vdc-130Vdc nom.)
Response time	(charging time) max. 4 s
Dimensions	H201.9mm x W117.1mm x D102.4mm H7.95" x W4.61" x D4.03"
Power consumption	(inrush) 1800 W (continuous) 180 W
Technical compatibility with	for A32/ASD32 (3200A) frame size
Power consumption	(inrush) 1800 VA (continuous) 180 VA
Order code / Manufacturer SKU	MD12NC 1800310
Manufacturer product status	Commercialized
Equivalent to	1800310

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

Documents

E-PLAN - NOARK - MD12NC - Part details

NOARK - Power Circuit Breakers and Non-Automatic Switches - Catalog.pdf

Access to all NOARK drawings

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com