

NOARK

# MD12ND

Motor operator - 1800311 - 3200A frame - 208-240Vdc/ac - for 3200A ACB/switch disconnector

Charging motor / remote operator - for A32/ASD32 (3200A) frame size - NOARK (A32 series) - 177-264Vac (208Vac-240Vac nom.) / 177-264Vdc (208Vdc-240Vdc nom.) supply voltage - equivalent to 1800311

## Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

## Specifications

| | |
|---|---|
| **Primary brand** | NOARK |
| **Main function** | Charging motor |
| **Product series / family name** | Electrical protection > ACBs and disconnector switches accessories > Motor operators |
| **Sub-range name** | A32 series |
| **Functions** | Charging motor / remote operator |
| **Supply voltage (AC)** | 177-264Vac (208Vac-240Vac nom.) |
| **Supply voltage (DC)** | 177-264Vdc (208Vdc-240Vdc nom.) |
| **Response time** | (charging time) max. 4 s |
| **Dimensions** | H201.9mm x W117.1mm x D102.4mm<br>H7.95" x W4.61" x D4.03" |
| **Power consumption** | (inrush) 1800 W<br>(continuous) 180 W |
| **Technical compatibility with** | for A32/ASD32 (3200A) frame size |
| **Power consumption** | (inrush) 1800 VA<br>(continuous) 180 VA |
| **Order code / Manufacturer SKU** | MD12ND<br>1800311 |
| **Manufacturer product status** | Commercialized |
| **Equivalent to** | 1800311 |

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

## Documents

E-PLAN - NOARK - MD12ND - Part details

NOARK - Power Circuit Breakers and Non-Automatic Switches - Catalog.pdf

Access to all NOARK drawings

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com