

NOARK

AXFC11Q

Auxiliary contact - 1314051 - Ex9CKT - mounts on 20-90A 3P cont. - 1NO+1NC - side mounting

Auxiliary contact block / switch block - mounts on 20-90A 3P cont. - NOARK (Ex9CKT series) - 1NO+1NC (1 Normally Open + 1 Normally Closed) aux. contacts - Quick connection - side mounting - equivalent to 1314051

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Auxiliary contact
Product series / family name	Industrial controls > Contactors > Definite purpose contactors > Accessories > Auxiliary contacts
Sub-range name	Ex9CKT series
Functions	Auxiliary contact block / switch block
Design	mounts on 20-90A 3P cont.
Rated current	3A (drop-out at 120Vac) 1.5A (drop-out at 240Vac) 0.75A (drop-out at 480Vac) 0.6A (drop-out at 600Vac) 30A (pick-up at 120Vac) 15A (pick-up at 240Vac) 7.5A (pick-up at 480Vac) 6A (pick-up at 600Vac) 10A (continuous at 120Vac/240Vac/480Vac/600Vac) 15A (125Vac or 250Vac) 4A (120Vac on lamp load) 0.5A (125Vdc) 0.25A (250Vdc)
Connection type	Quick connection
Mounting mode	side mounting
Normally Open (NO) auxliary contacts	1 NO contacts

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

Normally Closed (NC) auxiliary contacts	1 NC contacts
Contacts type	1NO+1NC (1 Normally Open + 1 Normally Closed) aux. contacts
Order code / Manufacturer SKU	AXFC11Q 1314051
Manufacturer product status	Commercialized
Equivalent to	1314051

Documents

NOARK - Industrial controls - Catalog.pdf

Access to all NOARK drawings

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com