

NOARK

SHT11NEF

Shunt trip release coil - 1800987 - 2500A frame - for ASD25 (2500A) switch disconnector

Shunt trip release coil - for ASD25 - NOARK (A25 series) - 266-484Vac (380Vac-440Vac nom.) control voltage - equivalent to 1800987

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Coil (Tripping)
Product series / family name	Electrical protection > ACBs and disconnector switches accessories > Auxiliary controls
Sub-range name	A25 series
Functions	Shunt trip release coil
Control Voltage (AC)	266-484Vac (380Vac-440Vac nom.)
Response time	(operating time) max. 50ms / 0.05 s
Power consumption	(inrush) 500 W (continuous) 4.5 W
Technical compatibility with	for ASD25
Power consumption	(inrush) 500 VA (continuous) 4.5 VA
Order code / Manufacturer SKU	SHT11NEF 1800987
Manufacturer product status	Commercialized
Equivalent to	1800987

Documents

NOARK - Power Circuit Breakers and Non-Automatic Switches - Catalog.pdf

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

SHT11NEF

Shunt trip release coil - 1800987 - 2500A frame - for ASD25 (2500A) switch disconnector

Access to all NOARK drawings

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com