NOARK

SHT12NB

Shunt trip release coil - 1800273 - 3200A frame - 48-60Vdc/ac - for 3200A ACB/switch disconnector

Shunt trip release coil - for A32/ASD32 (3200A) frame size - NOARK (A32 series) - 34-66Vdc (48Vdc-60Vdc nom.) / 34-66Vac (48Vac-60Vac nom.) control voltage - equivalent to 1800273

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Coil (Tripping)
Product series / family name	Electrical protection > ACBs and disconnector switches accessories > Auxiliary controls
Sub-range name	A32 series
Functions	Shunt trip release coil
Control Voltage (AC)	34-66Vac (48Vac-60Vac nom.)
Control Voltage (DC)	34-66Vdc (48Vdc-60Vdc nom.)
Response time	(operating time) max. 50ms / 0.05 s
Dimensions	H65.3mm x W35.3mm x D32mm H2.57" x W1.39" x D1.13"
Power consumption	(inrush) 500 W (continuous) 4.5 W
Technical compatibility with	for A32/ASD32 (3200A) frame size
Power consumption	(inrush) 500 VA (continuous) 4.5 VA
Order code / Manufacturer SKU	SHT12NB 1800273
Manufacturer product status	Commercialized
Equivalent to	1800273

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

Documents

NOARK - Power Circuit Breakers and Non-Automatic Switches - Catalog.pdf

Access to all NOARK drawings

E-PLAN - NOARK - SHT12NB - Part details

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com