

NOARK

SHT12NE

Shunt trip release coil - 1800447 - 3200A frame - 380-415Vac - for ASD25 (2500A) switch disconnector

Shunt trip release coil - for ASD25 - NOARK (A32 series) - 266-457Vac (380Vac-415Vac nom.) control voltage - equivalent to 1800447

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Coil (Tripping)
Product series / family name	Electrical protection > ACBs and disconnector switches accessories > Auxiliary controls
Sub-range name	A32 series
Functions	Shunt trip release coil
Control Voltage (AC)	266-457Vac (380Vac-415Vac nom.)
Response time	(operating time) max. 50ms / 0.05 s
Dimensions	H65.3mm x W35.3mm x D32mm H2.57" x W1.39" x D1.13"
Power consumption	(inrush) 500 W (continuous) 4.5 W
Technical compatibility with	for ASD25
Power consumption	(inrush) 500 VA (continuous) 4.5 VA
Order code / Manufacturer SKU	SHT12NE 1800447
Manufacturer product status	Commercialized
Equivalent to	1800447

Documents

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

SHT12NE

Shunt trip release coil - 1800447 - 3200A frame - 380-415Vac - for ASD25 (2500A) switch disconnector

NOARK - Power Circuit Breakers and Non-Automatic Switches - Catalog.pdf

Access to all NOARK drawings

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com