

NOARK

SHT21NB

Shunt trip release coil - 1100506 - 220-240Vac - for M1

Shunt trip release coil - for M1 frame size - NOARK - 220Vac-240Vac control voltage - equivalent to 1100506

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Coil (Tripping)
Product series / family name	Electrical protection > MCCBs and disconnector switches accessories > Auxiliary controls
Functions	Shunt trip release coil
Control Voltage (AC)	220Vac-240Vac
Response time	(operating time) 10-60ms / 0.01-0.06 s
Dimensions	H39.1mm x W29.5mm x D31.2mm H1.54" x W1.16" x D1.23"
Technical compatibility with	for M1 frame size
Order code / Manufacturer SKU	SHT21NB 1100506
Manufacturer product status	Commercialized
Equivalent to	1100506
Compliant with standard(s)	UL489 listed (file number E355392) CSA C22.2 No.5 IEC/EN 60947-2 CE marking RoHS compliant

Documents

NOARK - MCCB MCP MCS Ex9 series-M - Catalog.pdf

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

SHT21NB

Shunt trip release coil - 1100506 - 220-240Vac - for M1

Access to all NOARK drawings

E-PLAN - NOARK - SHT21NB - Part details

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com