

NOARK

SHT22ND

Shunt trip release coil - 1100516 - 480Vac-500Vac

Shunt trip release coil - for M2 / M3 frame size - NOARK - 480Vac-500Vac control voltage - equivalent to 1100516

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Coil (Tripping)
Product series / family name	Electrical protection > MCCBs and disconnector switches accessories > Auxiliary controls
Functions	Shunt trip release coil
Control Voltage (AC)	480Vac-500Vac 336-550Vac (pick-up voltage)
Response time	(operating time) 10-60ms / 0.01-0.06 s
Dimensions	H46.5mm x W36.8mm x D32mm H1.83" x W1.45" x D1.26"
Technical compatibility with	for M2 / M3 frame size
Order code / Manufacturer SKU	SHT22ND 1100516
Manufacturer product status	Commercialized
Equivalent to	1100516
Compliant with standard(s)	UL489 listed (file number E355392) CSA C22.2 No.5 IEC/EN 60947-2 CE marking RoHS compliant

Documents

NOARK - MCCB MCP MCS Ex9 series-M - Catalog.pdf

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

SHT22ND

Shunt trip release coil - 1100516 - 480Vac-500Vac

Access to all NOARK drawings

E-PLAN - NOARK - SHT22ND - Part details

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com