

NOARK

XF11NBF

Closing release coil - 1800964 - 2500A frame - 48-60Vdc/ac - for 2500A ACB/switch disconnector

Closing release coil - for A25/ASD25 (2500A) frame size - NOARK (A25 series) - 34-66Vdc (48Vdc-60Vdc nom.) / 34-66Vac (48Vac-60Vac nom.) control voltage - equivalent to 1800964

Additional information

The technical information provided in the datasheet is subject to change without notice. For confirmation, please contact NOARK's product support team.

Specifications

Primary brand	NOARK
Main function	Coil (closing)
Product series / family name	Electrical protection > ACBs and disconnector switches accessories > Auxiliary controls
Sub-range name	A25 series
Functions	Closing release coil
Control Voltage (AC)	34-66Vac (48Vac-60Vac nom.)
Control Voltage (DC)	34-66Vdc (48Vdc-60Vdc nom.)
Response time	(operating time) max. 50ms / 0.05 s
Power consumption	(inrush) 500 W (continuous) 4.5 W
Technical compatibility with	for A25/ASD25 (2500A) frame size
Power consumption	(inrush) 500 VA (continuous) 4.5 VA
Order code / Manufacturer SKU	XF11NBF 1800964
Manufacturer product status	Commercialized
Equivalent to	1800964

Documents

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com

XF11NBF

Closing release coil - 1800964 - 2500A frame - 48-60Vdc/ac - for 2500A ACB/switch disconnector

NOARK - Power Circuit Breakers and Non-Automatic Switches - Catalog.pdf

Access to all NOARK drawings

All rights reserved 2016-2026 to KYKLO and products.na.noark-electric.com